



ANDREA
COMMUNICATIONS

NC-185 VM USB

ON-EAR STEREO USB HEADSET



- Exclusive noise-canceling microphone meets the highest standards to receive the coveted "6 Dragon" rating for speech accuracy by Nuance
- Pro-Flex wire microphone boom for perfect placement
- 40 mm stereo speakers with deep bass sound deliver crystal clear audio
- Comfortable foam ear cushions
- Reversible for left or right side usage
- Stainless steel adjustable headband folds flat for storage
- Extra long 8-foot shielded cable with USB sound card and USB plug and convenient in-line volume and mute controls



PARAMETER	VALUE
Connections	
Power	USB
Microphone Input	1 Channel
Audio Output	2 Channel-stereo
Microphone	
Noise Cancellation	5 dB/octave
Frequency Range	100-10,000 Hz
Electrical Signal-to-Noise Ratio	> 60 dB
Sensitivity at 1kHz (0 dB=1V/Pa)	-44 dB
Current Consumption	< 0.5 mA
A/D Conversion Resolution	16 bit
THD + N	-76 dB
Speakers	
Frequency Range	50-20,000 Hz
Coil Resistance	32 ohm
Sound Output from 1kHz 1mW Input (0 dB=20 µPa)	114 dB
Maximum Input Power	40 mW
D/A Conversion Resolution	16 bit
THD + N	-71 dB



Andrea Communications LLC
140 Finn Court • Farmingdale, New York 11735
800.442.7787 • sales@andreacommunications.com
www.andreacommunications.com

